

Functional Devices, Inc. • p: 800.888.5538 • f: 765.883.7505 • www.functionaldevices.com • sales@functionaldevices.com

PSB40AB10

120 Vac Convenience Outlet *

0

!.

0

⊕0

24 Vac Breaker 24 Vac On/Off Switch

Neutral —

120 Vac —

Panel Mount 40 VA Power Supply, 120 to 24 Vac

- Ground

⊕ 0

0000

4 4 0

Com 24 Vac

10 Amp Main Breaker/Switch

000000

- 120 Vac Aux. Output

LED

PSB100AB10

-2.250"-

●⊕⊕⊕⊕●

⊙ ⊙

0000


Ų.

CN OFF

.⊕0

5.250

Panel Mount 100 VA Power Supply, 120 to 24 Vac





Specifications

 Transformer:
 One 40 VA Split-Bobbin (PSB40AB10) One 100 VA Split-Bobbin (PSB100AB10)

 Primary:
 120 Vac

 Secondary:
 24 Vac, w/ LED Indicator

 Frequency:
 50/60 Hz

 Over Current Protection:
 Inherently Limited + Circuit Breaker (PSB40AB10) Circuit Breaker (PSB100AB10)

 24 Vac ON/OFF:
 On / Off Switch

 Main Breaker ON/OFF:
 Switch / Breaker (10 Amp) (Kills power to entire unit: Outlets [if selected to be controlled by switch], Aux. Output, & Transformer) Total Combined Output 9A

 Mounting:
 Panel mount

 Approvals:
 Class 2 (UL Approved

 UL5085-3), UL916, UL508,
 C-UL, CE, RoHS

 Dimensions:
 5.200" x 5.250" x 3.750"

 Weight:
 2.18 lbs. (PSB40AB10)

 3.58 lbs. (PSB100AB10)

Notes:

 Move internal jumper to "HOT" position if you wish outlets to always be hot otherwise outlets will be switched by main breaker.*
 To order UL508, add "-IC" to end of model number.